


## Featured SimpleSpec


### 300.33

Lightbox Unframed Chroma



### 350.01

Lightbox Wall-to-Ceiling Chroma



## Introduction **3fit 3.0 White LED™**

- LED Life of approximately 50K hours, under normal operating conditions
- Low wattage, low heat, low voltage (24VDC Operation)
- Design prevents “scalloping” effect, providing consistent and uniform illumination
- Emits no UV or infrared light and does not contain lead, mercury, or glass, allowing for eco-friendly handling and disposal when required
- Simple user-friendly installation
- Conforms to UL 2108 Low Voltage Lighting Systems
- Adhesive Backed
- White LEDs are 4500K
- Exterior rated LEDs - IP65

## Table of Contents

### 3 Specifications

- 3 Dimensions - 3-60-765 96W Power Supply

### 4 SimpleSpec Solutions

- 4 Solution 1: SimpleSpec 300.33 Lightbox Unframed Chroma

### 5 Installation

- 5 Wiring Diagram for 3fit - White LEDs
- 6 Wiring Diagram for 3fit - 0-10V Dimming  $\leq 100W$
- 7 Wiring Diagram for 3fit - 0-10V Dimming 100W-1200W

# Direct Backlighting

## 3fit 3.0 White LED™

### Specifications

#### LEDs

Part Number	LED Color	Pucks/Segment	Color Temperature	Viewing Angle	Watts/Segment	Max Segments/Run	Max Pucks/Run	Volts
3-60-762	Natural White	66	4500K	140°	39.6W	2	132	24V

\*Photometric & Radiometric Quantities: Flux = 203.34 lm Eff.:100.19lm/W Fe = 635.29mW (measured on individual puck)  
IP65 Exterior Rated LED

#### Drivers

Part Number	Description	Dimensions	Input Voltage	Input Current	Output Power	Output Voltage	Output Current
3-60-497	0-10V Slide Control Wall Dimmer	-	-	-	-	-	-
3-60-765	96W Dimmable Power Supply	11.7"×2.36"×1.4"	120-277VAC	.8/.35	96	24	4



3-60-497 Slide Control




3-60-762 3fit LEDs, 66-Puck String, Natural White



3-60-765 Dimmable Power Supply

#### Dimensions - 3-60-765 - Dimmable Power Supply





# Direct Backlighting

## 3fit 3.0 White LED™

### Solution 1


SimpleSpec 300.33

Lightbox Unframed Chroma



#### Section View

\*Spacing of the lights is specific to the translucency of the resin. Contact 3form for more information.



White LED 3fit Overall View



3-60-762 3fit LEDs, 66-Puck String, Natural White




3-60-765 Dimmable Power Supply

\*Installation Wiring Diagram on page 5

\*An optional dimmer is also available - see dimming wiring diagrams on page 6 - page 7.

### Installation


#### Wiring Diagram for 3fit - White LEDs



**Note:** Wiring is as shown unless shown differently on 3form Lighting Layout Drawing

### Installation

#### Wiring Diagram for 3fit - 0-10V Dimming ≤100W



# Direct Backlighting

## 3fit 3.0 White LED™

### Installation

#### Wiring Diagram for 3fit - 0-10V Dimming 100W-1200W

